OSRAM

Lamps with metal bases H21W

Original spare part





The cost-effective original spare parts

ORIGINAL signal lamps with metal bases feature - like all ORIGINAL products from OSRAM - a reliable OEM quality. Due to the wide product range, the lamps can be used as original spare lamps for different applications.

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp

General Product Information


Electrical Data

Power input	25 W
Nominal voltage	12.0 V
Nominal wattage	21 W
Test voltage	13.5 V
Power input tolerance	±5 %

Photometric Data

Nominal luminous flux	600 lm
Luminous flux tolerance	±12 %

Physical Attributes & Dimensions



Diameter	9 mm
Product weight	2.68 g
Length	38.9 mm
Lamp base	BAY9s

Lifetime Data

Lifespan B3	240 hr
Lifespan Tc	480 hr

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	H21W
Approval marks – approval	E1 approval

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)			
Primary article identifier	4050300883335 4008321379382 4062172262316 4008321095190 4008321379320		
Candidate list substance 1	No declarable substances contained		
Declaration no. in SCIP database	No declarable substances contained		

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321095190	OSRA64136	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095190	ORIGINAL - METAL BASE H21W	Unpacked 1	9 mm x 9 mm x 38 mm	0.00 dm ³	3.00 g
4008321095213	ORIGINAL - METAL BASE H21W	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm ³	249.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

File



User instruction
GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















